

ST2221C

**Version : A.004
Issue Date : 2002/06/14
File Name : SP-ST2221C-A.004.doc
Total Pages : 17**

16-Bit Constant Current LED Drivers



新竹市科學園區展業一路 9 號 7 樓之 1

SILICON TOUCH TECHNOLOGY INC.

9-7F-1, Prosperity Road I, Science Based Industrial Park,
Hsin-Chu, Taiwan 300, R.O.C.

Tel : 886-3-5645656 Fax : 886-3-5645626

ST2221C

16-Bit Constant Current LED Drivers


General Description

The ST2221C is specifically designed for LED and LED DISPLAY constant current drivers. The value of constant current can be varied using an external resistor ($I_{out} = 5 \sim 90mA$). The devices include a 16-bit shift registers, latches, and constant current drivers on a single Silicon CMOS chip.


Features

- Constant Current Output : Current with one resistor for 5mA to 90mA
- Maximum Clock Frequency : 25MHz (Cascade Operation)
- 5V CMOS Compatible Input
- Package : DIP24 , SOP24, SSOP24
- Constant Current Matching: ($T_a = 25^{\circ}C$ 、 $V_{DD} = 5.0V$)
Bit-to-Bit: $\pm 6.0\%$ 、 Chip-to-Chip : $\pm 10.0\%$ 、
@ $I_{OUT} = 5 \sim 90mA$


Pin Connection (Top view)



Block Diagram



Timing Diagram



(Note) Latches are level sensitive (not edge triggered).

LATCH-terminal = H level, latches become transparent; LATCH-terminal = L level, latches hold data.

ENABLE-terminal = H level, all outputs (OUT0~15) are off.





An external resistor is connected between R-EXT and GND for setting up the value of constant current.

SERIAL-OUT changes state on the falling edges of clock.

Pin Description

PIN No.	PIN NAME	FUNCTION
1	GND	Ground terminal
2	SERIAL-IN	Input terminal of a data shift register
3	CLOCK	Input terminal of a clock for shift register
4	LATCH	Input terminal of data strobe
5~20	OUT0~15	Output terminals
21	ENABLE	Input terminal of output enable (active low)
22	SERIAL-OUT	Output terminal of a data shift register
23	R-EXT	Input terminal of an external resistor
24	V _{DD}	5V Supply voltage terminal

Equivalent Circuit of Inputs and Outputs

1. ENABLE terminal**2. LATCH terminal****3. CLOCK, SERIAL-IN terminal****4. SERIAL-OUT terminal**



Maximum Ratings ($T_a = 25^\circ\text{C}$, $T_{j(\max)} = 140^\circ\text{C}$)

CHARACTERISTIC	SYMBOL	RATING	UNIT
Supply Voltage	VDD	0 ~ 7.0	V
Input Voltage	VIN	-0.4 ~ VDD+0.4	V
Output Current	IOUT	90	mA
Output Voltage	VOUT	-0.5 ~ 9.5	V
Clock Frequency	fCLK	25	MHz
GND Terminal Current	IGND	1440	mA
Power Dissipation	PD	2.87 (DIP-24 : $T_a=25^\circ\text{C}$)	W
		1.45 (SOP-24 : $T_a=25^\circ\text{C}$)	
		1.27 (SSOP-24 : $T_a=25^\circ\text{C}$)	
Thermal Resistance	R _{th(j-a)}	40.0 (DIP-24)	°C/W
		79.2 (SOP-24)	
		90.2 (SSOP-24)	
Storage Temperature	T _{stg}	-55 ~ 150	°C

Recommended Operating Condition

CHARACTERISTIC	SYMBOL	CONDITION	MIN.	TYP.	MAX.	UNIT
Supply Voltage	VDD	—	4.5	5.0	5.5	V
Output Voltage	VOUT	—	—	—	9	V
Operating temperature	T _{OPR}	—	-40	—	85	°C
Output Current	IO	OUTn	5	—	85	mA
	IOH	SERIAL-OUT	—	—	1.0	
	IOL	SERIAL-OUT	—	—	-1.0	
Input Voltage	VIH	—	0.7VDD	—	VDD+0.3	V
	VIL	—	-0.3	—	0.3VDD	
LATCH Pulse Width	tw LAT	VDD = 4.5 ~ 5.5 V	15	—	—	ns
CLOCK Pulse Width	tw CLK		15	—	—	ns
Set-up Time for DATA	tsetup(D)		20	—	—	ns
Hold Time for DATA	thold(D)		20	—	—	ns
Set-up Time for LATCH	tsetup(L)		15	—	—	ns
Clock Frequency	fCLK	Cascade operation	—	—	25	MHz
Power Dissipation	PD	Ta = 85°C (DIP-24)	—	—	1.37	W
		Ta = 85°C (SOP-24)	—	—	0.69	
		Ta = 85°C (SSOP-24)	—	—	0.61	



Electrical Characteristics (VDD = 5.0 V, Ta = 25°C unless otherwise noted)

CHARACTERISTIC	SYMBOL	CONDITION	MIN.	TYP.	MAX.	UNIT
Input Voltage "H" Level	VIH	—	0.7VDD	—	VDD	V
Input Voltage "L" Level	VIL	—	GND	—	0.3VDD	
Output Leakage Current	IOH	VOH = 9.5 V	—	—	1.0	uA
Output Voltage (S - OUT)	VOL	IOL = 1.0 mA	—	—	0.4	V
	VOH	IOH = -1.0 mA	4.6	—	—	
Output Current (Bit-Bit)	IOL1	VOUT = 0.7±0.25V REXT = 910Ω	—	3	6	%
	IOL2	VOUT = 0.7±0.25V REXT = 360Ω	—	3	6	
Output Current (Chip-Chip)	IOL3	VOUT = 0.7V REXT = 910Ω	—	5	10	
	IOL4	VOUT = 0.7V REXT = 360Ω	—	5	10	
Supply Voltage Regulation	% / VDD	REXT = 470Ω, Ta = -40 ~ 85°C	—	1.5	5.0	% / V
Pull-Up Resistor	RIN(up)	—	150	300	600	KΩ
Pull-Down Resistor	RIN(down)	—	100	200	400	KΩ
Supply Current "OFF"	IDD(off)1	REXT = OPEN, OUT0~7 = off	—	0.3	0.6	mA
	IDD(off)2	REXT = 470Ω, OUT0~7 = off	3.9	5.5	7.7	
Supply Current "ON"	IDD(off)3	REXT = 250Ω, OUT0~7 = off	7.2	10.1	14.1	
	IDD(on)1	REXT = 470Ω, OUT0~7 = on	3.9	5.5	7.7	
	IDD(on)2	REXT = 250Ω, OUT0~7 = on	7.2	10.1	14.1	


Switching Characteristics (Ta = 25 °C unless otherwise noted)

CHARACTERISTIC	SYMBOL	CONDITION	MIN.	TYP.	MAX.	UNIT	
Propagation Delay Time ("L" to "H")	SIN-OUT _n	tpl _H	VDD=5.0V VIH=VDD VIL=GND REXT=470Ω ¹ VL=3.0V RL=65Ω	—	450	550	ns
	LATCH-OUT _n		—	450	550		
	ENABLE-OUT _n		—	450	550		
	CLK-SOUT		—	15	20		
Propagation Delay Time ("H" to "L")	SIN-OUT _n	tp _H L	CL=13pF	—	20	40	ns
	LATCH-OUT _n			—	20	40	
	ENABLE-OUT _n			—	20	40	
	CLK-SOUT			—	15	20	
Output Current Rise Time	tor			—	450	550	ns
Output Current Fall Time	tof			—	20	40	ns


¹ Delay time tp_{LH} and Rise Time tor will both increase as the $Rext$ value increased.

Test Circuit

DC characteristic




AC characteristic




Timing Diagram


1. CLOCK-SERIAL-IN, SERIAL-OUT, OUTn













2. CLOCK-LATCH







3. ENABLE-OUTn









Note

As the power dissipation of a semiconductor chip is limited by its package and ambient temperature, this device requires a maximum output current to be calculated for a given operating condition. The maximum allowable power consumption (P_d (max)) of this device is calculated as follows:

$$P_d(\text{max})(\text{Watt}) = \frac{(T_j(\text{junction temperature}) (\text{max}) - T_a(\text{ambient temperature}))(\text{°C})}{R_{th} (\text{°C / Watt})}$$

Based on the P_d (max), the maximum allowable current can be calculated as follows:

$$I_{out} = (P_d - V_{DD} \cdot I_{DD}) / (\# \text{ outputs} \cdot V_o \cdot \text{Duty})$$

System Configuration Example

[1] Output current (I_{OUT})


Sink current is set by the external resistor as shown in the figure (I_{out} vs. R_{ext}).

[2] LED supply voltage (V_{LED}) setup

$$V_{LED} = V_{CE} (\text{Tr } V_{sat}) + V_f (\text{LED forward voltage}) + V_o (\text{IC supply voltage})$$

To prevent too much power dissipated by the device due to higher V_{LED} , an additional R can be used to reduce the Vout when the outputs consume current:

$$R = \frac{V_{LED} - V_{CE} - V_f - V_o(\min)}{I_o(\max) * Bit(\max)}$$



Note

This device has only one ground pin shared by signal, output sink current, and power ground. It is advisable to pattern the ground layout with minimized inductance such that the switching noise induced by the input signals and the output sink current would not cause chip malfunction. To prevent the drivers' outputs from damage by overshoot stress, it is also advisable not to turn off the drivers and scan transistors simultaneously.




點晶科技股份有限公司
SITI SILICON TOUCH TECHNOLOGY INC.

ST2221C

Package Outline

P-DIP 24

UNIT : INCH






點晶科技股份有限公司
SILICON TOUCH TECHNOLOGY INC.

ST2221C

Package Outline

SOP24

UNIT : INCH






點晶科技股份有限公司
SILICON TOUCH TECHNOLOGY INC.

ST2221C

Package Outline

SSOP24

UNIT : INCH





點晶科技股份有限公司

SITI

SILICON TOUCH TECHNOLOGY INC.

ST2221C

The products listed herein are designed for ordinary electronic applications, such as electrical appliances, audio-visual equipment, communications devices and so on. Hence, it is advisable that the devices should not be used in medical instruments, surgical implants, aerospace machinery, nuclear power control systems, disaster/crime-prevention equipment and the like. Misusing those products may directly or indirectly endanger human life, or cause injury and property loss.

Silicon Touch Technology, Inc. will not take any responsibilities regarding the misusage of the products mentioned above. Anyone who purchases any products described herein with the above-mentioned intention or with such misused applications should accept full responsibility and indemnify. Silicon Touch Technology, Inc. and its distributors and all their officers and employees shall defend jointly and severally against any and all claims and litigation and all damages, cost and expenses associated with such intention and manipulation.